

boltswitch



100 - 200 AMP PULLOUT SWITCH (200 AMP FRAME SIZE)





VOLTAGE	AMPACITY	CATALOG NUMBERS	
		2-POLE*	3-POLE
240 AC/125 DC	100	PTL223	PTL323
	200	PT224	PT324
600 AC	200	PT264	PT364

^{* 2-}pole units are also available in 3-pole construction with center pole omitted. Catalog numbers are the same as 3-pole with suffix "-2P". (Example: PT324-2P)

APPLICATION: These devices are load-break switches designed primarily for

installation in panelboards, control panels, and meter banks. They

receive Class T fuses.

TESTS: Tested in accordance with UL 1429, and listed as "Pullout Switches"

under file No. E131005. UL and C-UL listed for use on circuits having available fault currents of 200,000 RMS symmetrical amperes. DC Rated switches are UL and C-UL Listed for use on circuits capable

of delivering 50,000 amperes at 125 VDC.

FEATURES:

